

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE
Certification under 37 CFR §1.10 (if applicable)

EL 530 368 614 US
Express Mail Label Number

May 30, 2000
Date of Deposit

I hereby certify that this Transmittal Letter, enclosed application and any other documents referred to as enclosed herein, are being deposited in an envelope with the United States Postal Service "Express Mail Post Office to Addressee" service under 37 CFR §1.10 on the date indicated above and addressed to the Assistant Commissioner for Patents, Washington, D.C. 20231.

Matthew D. Redlon
(Print Name of Person Mailing Application)

(Signature)
(Signature of Person Mailing Application)

Transmittal of Utility Patent Application
for Filing Under 37 CFR §1.53(b)

Box Patent Application
Assistant Commissioner for Patents
Washington, D.C. 20231

Sir:

Transmitted herewith for filing is a utility patent application by inventor William Lo, and entitled:

REDUCED PIN GIGABIT MEDIA INDEPENDENT INTERFACE

1. Enclosed are:

- ☒ This Transmittal letter
- ☒ One stamped, self-addressed postcard for PTO date stamp
- ☒ Certificate of Express Mail
- ☒ One utility patent application containing text pages 1-48 and
 - ☒ 5 Sheets of drawings
- ☒ Declaration of inventorship
- ☒ 2 Assignment(s) for recordation with transmittal sheets
- ☒ A Small Entity Statement

2. U.S. Priority

- ☐ This application is a of Ser. No. filed.
- ☒ Conditional Petition for Extension of Time: An Extension of Time is requested to provide for timely filing if required to establish copendency with the parent after all papers filed herewith have been considered.

3. Foreign Priority

- ☐ Priority of Application No. filed in on is claimed under 35 USC §119.
- ☐ A certified copy of this priority document is enclosed.

4. Fees

The filing fee has been calculated as shown below:

For:	(Col. 1)	(Col. 2)	Small Entity			Other Than a Small Entity	
	No. Filed	No. Extra	Rate	Fee		Rate	Fee
Basic Fee				\$345.00	or		\$690.00
Total Claims	108 - 20	88	88 x \$ 9 =	\$792.00	or	x \$ 18 =	\$
Independent Claims	16 - 3	13	13 x \$39 =	\$507.00	or	x \$ 78 =	\$
<input type="checkbox"/> Multiple Dependent Claim Presented			+ \$130 =	\$	or	+ \$260 =	\$
* If the difference in Col. 1 is less than zero, enter "0" in Col. 2.							\$
			TOTAL	\$1644.00	or	TOTAL	

- ☒ A check for \$1724.00 is enclosed to cover the Filing Fee and Assignment Fee.
- ☒ The Commissioner is hereby authorized to charge any underpayment of fees (or credit any overpayment) to Deposit Account 04-0531.

Respectfully submitted,

Michael T. Gabrik

Michael T. Gabrik
Registration No. 32,896

Date: 5/30/2000

Correspondence Address:

Customer No. 22918

Attorney Docket No.: 5700-0005/MP0050

Applicant(s): William Lo

Serial No.: Not yet Assigned

Filing Date: Concurrently Herewith

For: **REDUCED PIN GIGABIT MEDIA INDEPENDENT INTERFACE**

Small Entity Statement Under
37 CFR 1.9(f) and 1.27(c) - Small Business Concern

I hereby declare that I am:

- ☐ The owner of the small business concern identified below:
- ☒ An official of the small business concern empowered to act on behalf of the concern identified below:

Name of Concern: **Marvell Technology Group, LTD**

Address of Concern: **Clarendon House, 2 Church Street, P.O. Box 1022,
Hamilton HM DX, Bermuda**

I hereby declare that the above-identified small business concern qualifies as a small business concern as defined in 13 CFR §121.12, and reproduced in 37 CFR §1.9(d), for purposes of paying reduced fees under 35 U.S.C. §41 in that the number of employees, including those of its affiliates, does not exceed 500 persons and the concern has not assigned, granted, conveyed, or licensed, and is under no obligation under contract or law to assign, grant, convey, or license, any rights in the invention to any person who could not be classified as an independent inventor if that person had made the invention, or to any concern which would not qualify as a small business concern or a nonprofit organization under this section. For this section, concerns are affiliates of each other when either, directly or indirectly, one concern controls or has the power to control the other, or a third party or parties controls or has the power to control both. The number of employees of the business concern is the average over the fiscal year of the persons employed during each of the pay periods of the fiscal year. Employees are those persons employed on a full-time, part-time or temporary basis during the previous fiscal year of the concern. I hereby declare that rights under contract or law in the above-identified application have been conveyed to and remain with the small business concern identified above.

If the rights held by the above-identified small business concern are not exclusive, each individual, concern or organization having rights to the invention is listed below* and no rights to the invention are held by any person, other than the inventor, who could not qualify as a small business concern under 37 CFR §1.9(d) or by any concern which would not qualify as an independent inventor under 37 CFR §1.9(c) if that person made the invention, or by any concern which would not qualify as a small business concern under 37 CFR §1.9(d) or a nonprofit organization under 37 CFR §1.9(e).

NOTE: Separate statements are required from each named person, concern or organization having rights to the invention averring to their status as small entities. (37 CFR §1.27).

Name: _____

Address: _____

☐ individual ☐ small business concern ☐ nonprofit organization

I acknowledge the duty to file, in this application or patent, notification of any change in status resulting in loss of entitlement to small entity status prior to paying, or at the time of paying, the earliest of the issue fee or any maintenance fee due after the date on which status as a small entity is no longer appropriate (37 CFR §1.28(b)).

Transmittal of Utility Patent Application for Filing

Certification Under 37 C.F.R. §1.10 (if applicable)


EL 530 368 614 US
"Express Mail" Label Number

May 30, 2000
Date of Deposit

I hereby certify that this application, and any other documents referred to as enclosed herein are being deposited in an envelope with the United States Postal Service "Express Mail Post Office to Addressee" service under 37 CFR §1.10 on the date indicated above and addressed to the Assistant Commissioner for Patents, Washington, D.C. 20231

Matthew D. Redlon

(Print Name of Person Mailing Application)



(Signature of Person Mailing Application)

REDUCED PIN GIGABIT MEDIA INDEPENDENT INTERFACE

Incorporation by Reference

IEEE standard 802.3, including all of its sections, is incorporated by reference herein in its entirety.

Field of the Invention

The present invention relates to a reduced pin (gigabit) media independent interface, and a method of forming such an interface. More particularly, the invention relates to signal encoding and decoding techniques for reducing interface pin count.

Background of the Invention

Interconnections between computers, peripheral devices, and Internet appliances (referred to as network clients) are ubiquitous. With networks firmly established in everyday life, there is now more demand in the form of increased data transfer rate and functionality being placed on the network switches and

other hardware which facilitate network communication to support more complex applications such as multimedia. As a result, the integrated circuits (ICs) in these components are becoming more highly integrated and complex to meet this demand. One problem is that added complexity tends to increase external connections or pin count.

Conventional networks may utilize twisted pair cable such as Category 5 and operate at a data rate of either 10 megabits per second (Mb/s) which generally complies with IEEE Standard 802.3, section 14, commonly known as 10BASE-T, and 100 Mb/s which generally complies with IEEE Standard 802.3, sections 24 and 25, commonly known as 100BASE-TX. With the demand for increased data transfer rates, a newer networking standard has been proposed that utilizes twisted pair cable and operates at a nominal data transfer rate of 1 gigabit (1000 megabits) per second. The 1 gigabit per second (Gb/s) transfer rate complies with IEEE Standard 802.3, section 40, commonly known as 1000BASE-T.

These two standards have different requirements and interfaces. When the network is operated in accordance with 10BASE-T or 100BASE-TX, the interface for interconnecting controllers and transceivers is defined in accordance with the a Media Independent Interface (MII). In either a 10BASE-T or a 100BASE-TX system, MII requires 16 connection lines or pins connecting the IC embodying the physical layers (PHY) to the IC embodying the media access controller layers (MAC). When the network is operated at a higher transmission rate in accordance with 1000BASE-T, the interface is defined by the Gigabit MII (GMII). 24 connection lines or pins are required for 1000BASE-T.

The pin count problem in such systems becomes more apparent when we consider that a typical network switch has n ports,

where n is the number of PHY and MAC layers respectively. Since the n MACs are typically fabricated as a single integrated circuit, the number of pins are $24 \times n$. For example, if there are 24 ports then the n MACs requires 24×24 or 576 pins. A higher number of pins result in a larger die, a larger package, a more complicated integrated circuit and higher costs, particularly at the higher data transfer rates.

Various attempts have been made to solve the above-mentioned problem. Two *ad hoc* standards, namely Reduced Media Independent Interface (RMII) and Serial Media Independent Interface (SMII) reduce the number of pins by serialization techniques for 10BASE-T and 100BASE-TX. The RMII technique requires 7 pins per port and the frequency doubles from 25 MHz to 50 MHz. Thus, for a 24 port switch 7×24 or 168 pins are required. The SMII technique requires 2 pins per port plus 1 synchronizing pin, and the frequency increases five fold from 25 MHz to 125 MHz. In the SMII technique $2 \times 24 + 1$ or 49 pins are required. As will be appreciated by those of ordinary skill in the art, these techniques operate at frequencies in which clock recovery between the PHY and MAC layers is not required.

While RMII and SMII provide reduced pin count interfaces, they are only applicable to 10BASE-T and 100BASE-TX systems. Thus, there is a need for an effective interface that reduces pin or connection count in a 1000BASE-T system without compromising functionality, and that also has the flexibility to be used in 10BASE-T and 100BASE-TX systems as well.

Objects and Summary of the Invention

It is therefore an object of this invention to provide a network interface which reduces the number of pins or connections without compromising functionality.

It is a further object of this invention to provide a reduced pin media independent interface, such as a reduced pin gigabit media independent interface (reduced pin GMII).

According to one aspect of the invention, a method of encoding signals for a network device is provided. The method comprises the steps of transmitting a clock signal; forming a transmit control signal comprising in one half of a cycle of the clock signal a transmit enable signal and comprising in the other half of the cycle of the clock signal a transmit error signal; transmitting the transmit control signal; and transmitting a data signal.

The signal encoding is preferably as follows. When the transmit enable signal is asserted, the data signal comprises one of packet data and symbol error data. When neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises idle data. When the transmit enable signal is asserted and the transmit error signal is not asserted in a cycle of the clock signal, the data signal comprises packet data. When both the transmit enable signal and the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises symbol error data. When the transmit enable signal is not asserted and the transmit error signal is asserted in a cycle of the clock signal, the data signal comprises one of carrier extension data and carrier extension data with error.

According to another aspect, the invention involves a method of decoding signals for a network device, comprising the steps of receiving a clock signal; receiving a receive control signal; decoding the receive control signal comprising in one half of a cycle of the clock signal a receive data valid signal or a carrier sense signal and in the other half of the cycle of the clock signal a receive error signal; and receiving a data signal.

The method preferably further comprising the step of decoding a preamble from the received data signal.

The signal decoding is preferably as follows. When the one half of the receive control signal is in a first state (i.e., not asserted) and the other half of the receive control signal is in the first state, the preamble is set to a first condition (e.g., not present). When the one half of the receive control signal is in a second state (i.e., asserted), the other half of the receive control signal is in the first state, and the preamble is in the first condition, a carrier sense signal is in the second state. When the one half of the receive control signal is in the second state, the other half of the receive control signal is in the first state, the preamble is in the first condition, and the received data signal comprises first predetermined data, then the preamble is set to the second condition and subsequent received data is decoded. When the one half of the receive control signal is in the second state, the other half of the receive control signal is in the first state, and the preamble is in a second condition (i.e., present), then the received data signal comprises packet data. When the one half of the receive control signal is in the second state, the other half of the receive control signal is in the second state, and the received data signal comprises second predetermined data, then a false carrier is asserted. When the one half of the receive control signal is in the second state, the other half of the receive control signal is in the second state, and the received data signal comprises first predetermined data, then a symbol error is asserted. When the one half of the receive control signal is in the first state, the other half of the receive control signal is in the second state, and the received data signal comprises one of third and fourth predetermined data, then the preamble is set to the first condition and a carrier extension is asserted.

According to a further aspect of the invention, a method of decoding signals for a network device is provided. The method comprises the steps of receiving a clock signal; receiving a transmit control signal; decoding the transmit control signal comprising in a half of a cycle of the clock signal a transmit enable signal and in the other half of the cycle of the clock signal a transmit error signal; and receiving a data signal.

The decoding scheme is preferably as follows. When the transmit enable is asserted, the data signal comprises one of packet data and symbol error data. When neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises idle data. When the transmit enable signal is asserted and the transmit error signal is not asserted in a cycle of the clock signal, the data signal comprises packet data. When both the transmit enable signal and the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises a symbol error data. When the transmit enable signal is not asserted and the transmit error signal is asserted in a cycle of the clock signal, the data signal comprises one of carrier extension data and carrier extension data with error.

According to still another aspect, the invention involves a method of encoding signals for a network device, comprising the steps of transmitting a clock signal; encoding a receive control signal comprising in one half of a cycle of the clock signal a receive data valid signal or a carrier sense signal and in the other half of the cycle of the clock signal a receive error signal; transmitting the receive control signal; and transmitting a data signal.

The method preferably further comprises the step of encoding a preamble for the data signal.

5 The encoding scheme is preferably as follows. When a carrier sense signal is in a second state (i.e., asserted), the one half of the receive control signal is set to the second state, and the other half of the receive control signal is set to a first state (i.e., not asserted). When a subsequent data signal containing packet data is to be transmitted, the one half of the receive control signal is set to the second state, the other half of the receive control signal is set to the first state, and a current data signal is set to first predetermined data. When the data signal comprises packet data, the one half of the receive control signal is set to the second state, and the other half of the receive control signal is set to the first state. When a false carrier is asserted, the one half of the receive control signal is set to the second state, the other half of the receive control signal is set to the second state, and the received data signal is set to second predetermined data. When a symbol error is asserted, the one half of the received control signal is set to the second state, the second half of the receive control signal is set to the second state, and the receive data signal is set to first predetermined data. When a carrier extension is asserted, the one half of the receive control signal is set to the first state, the other half of the receive control signal is set to the second state, and the received data signal is set to one of third and fourth predetermined data.

25 Other aspects of the invention include various networking devices for implementing the signal encoding and/or decoding schemes described above, and an interface signaling protocol by which the signal encoding/decoding schemes operate.

30 Other objects and attainments together with a fuller understanding of the invention will become apparent and appreciated by referring to the following description and claims taken in conjunction with the accompanying drawings.

Brief Description of the Drawings

Fig. 1 is a schematic diagram of a networking system in which aspects of the present invention may be employed.

Fig. 2 is a schematic diagram of another networking system in which aspects of the present invention may be employed.

Fig. 3 is a detailed schematic diagram of an interface between a media access controller (MAC) and a physical layer (PHY) in accordance with an embodiment of the invention.

Fig. 4 is a detailed schematic diagram of an interface between a media access controller (MAC) and a physical layer (PHY) in accordance with another embodiment of the invention.

Fig. 5 is a timing diagram illustrating the relationship between a control signal and its corresponding clock signal in accordance with embodiments of the invention.

Detailed Description of the Invention

Fig. 1 is schematic diagram of a typical networking system in which embodiments of the present invention may be employed. A computer 10 is connected to a first port of switch 20 via a communications channel, such as, twisted pair cable 30. Switch 20 may comprise 24 ports, to allow computer 10 to communicate with other computers, peripherals, network appliances and other networks. As will be appreciated by one of ordinary skill in the art, communication channel 30 may be implemented using a variety of techniques, such as wired, wireless, radio frequency, optical or the like.

Computer 10 comprises a media access controller or MAC 12 and physical layer interface (PHY) or transceiver 16, which are connected to each other by an interface defined by, for example, the MII for 10BASE-T standard and for 100BASE-TX standard, or the GMII for 1000BASE-T standard. MII for 10BASE-T standard and

for 100BASE-TX standard are discussed at IEEE standard 802.3, section 22. The Gigabit Media Independent Interface (GMII) is defined by IEEE 802.3 section 35. Both of these sections of IEEE 802.3 are incorporated by reference herein.

5 MAC 12 controls media access of transmitting and receiving packets to and from computer 10. Typically for gigabit level products, MAC 12 and PHY 16 are implemented as individual integrated circuits.

10 Switch 20 comprises MAC 22_n and PHY 26_n, which are respectively connected to each other in accordance with an interface as defined above. MAC 22_n and PHY 26_n are functionally similar to MAC 12 and PHY 16 of computer 10.

15 If MII is used, data is passed to and from MAC 22_n in 4 bit wide nibbles. The nibbles are converted to and from 10BASE-T or 100BASE-TX on the network side. If GMII is used, data is passed to and from MAC 22_n in 8 bit wide bytes. The bytes are converted to and from 1000BASE-T on the network side. Note that if fiber is used on the network side then the bytes are converted to and from 1000BASE-X on the network side. In other words, the MII/GMII provides a standard interface from a MAC to a transceiver regardless of the actual protocol used on the network side.

20 Referring now to Fig. 2, another networking environment in which the present invention may be practiced is illustrated. As shown in Fig. 2, computer 10 is connected to a first port of switch 20' via a communications channel, such as twisted pair cable 30. Switch 20' may comprise 24 ports to allow computer 10 to communicate with other computers, peripherals, network appliances and other networks.

30 Computer 10 comprises a media access controller or (MAC) 12 and physical layer interface (PHY) or transceiver 16, which are connected to each other in accordance with an interface, such

as, MII or GMII discussed above. MAC 12, computer 10, and PHY 16 are similar to those described above in connection with Fig. 1.

Switch 20' comprises n ports. Each of the n ports comprises MAC 22' $_n$ and PHY 26' $_n$. PHY 26' $_n$ comprises serializer interface 27 $_n$, and MAC 22' $_n$ comprises serializer interface 28 $_n$, which are connected to each other to facilitate communication between MAC 22' $_n$ and PHY 26' $_n$. Serializer interfaces 28 $_1$ - 28 $_n$ and MACs 22' $_1$ - 22' $_n$ are fabricated on a single integrated circuit. PHY 26' $_n$ and serializer interface 27 $_n$ are fabricated on another integrated circuit.

Referring now to Fig. 3, a schematic diagram of a reduced pin interface 32 constructed in accordance with an embodiment of the invention is illustrated. In this embodiment, interface 32 reduces the number of pins or connections in an MII interface between a MAC 22 $_n$ /22' $_n$ and a PHY 26 $_n$ /26' $_n$ by encoding and decoding various MII signals, as described below.

Conventional MII design includes five groups of signals: transmit signals, receive signals, control signals, management signals and power. As shown in Fig. 3, the transmit signals include a nibble-wide Transmit Data (TXD [3:0]), plus associated Transmit Clock (TX_CLK), Transmit Enable (TX_EN), and Transmit Error (TX_ER) signals. The data is synchronous with the clock, which has a rate one-fourth that of the data rate (that is, 25 MHz for a 100 Mb/s Ethernet and 2.5 MHz for a 10 Mb/s Ethernet). Transmit signals are used to move data from the controller to the transceiver for encoding and transmission on the LAN.

As shown in Fig. 3, MII receive signals include a nibble-wide Receive Data (RXD [3:0]), plus associated Receive Clock (RX_CLK), Receive Data Valid (RX_DV), and Receive Error (RX_ER) signals. The data is synchronous with the clock, the rate of which is one-fourth that of the data rate. Receive signals are

used to move decoded data from the transceiver to the controller.

Ethernet control signals include Carrier Sense (CRS) and Collision Detect (COL) signals generated by the transceiver and used by the controller for medium access control, as shown in Fig. 3. These signals are used only in half-duplex mode; they are ignored in full-duplex mode.

There are two management signals (not shown), which include a serial management I/O signal (MDIO) and an associated clock (MDC). Management information is exchanged (bidirectionally) between the controller and the transceiver for configuration and control.

A VDC power supply (not shown) is provided by the controller for operating the transceiver. A return path is provided for both the power and the logic signals.

In accordance with this embodiment of the invention, interface 32 employs the following signals: TXD [3:0], TX_CLK, TX_CTRL, RXD [3:0], RX_CLK, and RX_CTRL to reduce the interface connections or pins between MAC 22_n/22'_n and PHY 26_n/26'_n. TX_CTRL and RX_CTRL are control signals that are used to carry information previously carried on multiple signals. TX_CTRL and RX_CTRL run at either a rate of 5 Mb/s in which case TX_CLK and RX_CLK run at 2.5 MHz, or at rate of 50 Mb/s in which case TX_CLK and RX_CLK run at 25 MHz. The relationship between each of these CTRL signals and its corresponding CLK signal is illustrated by the timing diagram in Fig. 5.

On its interface transmit side, MAC 22_n/22'_n comprises a plurality of transmitting circuits including a data signal transmitter 42 that transmits TXD [3:0], a clock transmitter 44 that transmits TX_CLK, and a control signal transmitter 46 that transmits an encoded TX_CTRL signal. MAC 22_n/22'_n also includes

an encoder 48 that forms the encoded TX_CTRL signal, as described below.

A corresponding set of receiver circuits are provided on the interface receive side of PHY 26_n/26'_n. These circuits include a data signal receiver 52 that receives the TXD [3:0], a clock receiver 54 that receives TX_CLK, and a control signal receiver 56 that receives the encoded TX_CTRL signal. PHY 26_n/26'_n also includes a decoder that decodes TX_CTRL, as described below.

TX_CTRL alternates between transmitting TX_EN and TX_ER. In a preferred embodiment, the encoding is as follows. When TX_CTRL is 0 during a full TX_CLK cycle, any data on the data lines is idle data. When TX_CTRL is 1 during one (e.g., the first) half of a TX_CLK cycle, the type of data on the data lines depends on the value of TX_CTRL during the other (e.g., the second) half of that TX_CLK cycle and the bits on the data lines. A TX_CTRL value of 0 during the other half of the TX_CLK cycle for any data on the data lines indicates that such data is packet data. A TX_CTRL value of 1 during the other half of the TX_CLK cycle with the data lines carrying a 0101 sequence means that such data is symbol error data. The signal encoding/decoding is summarized in the table below.

One (e.g., first) half of TX_CLK	Other (e.g., second) half of TX_CLK		
TX_CTRL	TX_CTRL	TXD [3:0]	Definition
0	0	xxxx	Idle
0	0	xxxv	Inband signaling v 0 = 10BASE-T 1 = 100BASE-TX
1	0	xxxx	Packet Data
1	1	0101	Symbol Error

Turning now to the receive signals, on its interface receive side, MAC 22_n/22'_n comprises a plurality of receiver circuits including a data signal receiver 62 that receives RXD [3:0], a clock receiver 64 that receives RX_CLK, and a control signal receiver 66 that receives an encoded RX_CTRL signal. MAC 22_n/22'_n also includes a decoder 68 that is in communication with a state machine controller 69 for decoding the encoded RX_CTRL signal, as described below.

Corresponding transmitter circuits are provided on the interface transmit side of PHY 26_n/26'_n. Such circuits include a data signal transmitter 72 that transmits RXD [3:0], a clock transmitter 74 that transmits RX_CLK, and a control signal transmitter 76 that transmits the encoded RX_CTRL signal. PHY 26_n/26'_n also includes an encoder 78 that operates in connection with a state machine controller 79 to encode the RX_CTRL signal.

In the encoding/decoding scheme, the logical OR of RX_DV and CRS is carried by RX_CTRL in one (e.g., the first) half of a cycle of RX_CLK, and RX_ER is carried by RX_CTRL in the other (e.g., the second) half of that RX_CLK cycle. To distinguish between RX_DV and CRS, RXD [3:0] is decoded by the controller.

Normally, CRS is asserted before RX_DV. Hence, during the time between assertion of CRS and assertion of RX_DV, RXD [3:0] should be 0000. Since a packet of data starts with a 0101 pattern, the assertion of RX_DV can be denoted by a transition of RXD [3:0] from 0000 to 0101. An error condition may occur which causes CRS to assert. This is known as a false carrier which can be denoted by a transition of RXD [3:0] from 0000 to 1010.

The signal encoding/decoding scheme for the receive signals is described by a state machine algorithm implemented by state machine controllers 69 and 79 as set forth in the table below. It should be noted that a preamble is an initial eight bit sequence of 10101010 of an uncoded data packet.

One (e.g., first) half of RX_CLK	Other (e.g., second) half of X_CLK			
RX_CTRL	RX_CTRL	RXD [3:0]	Preamble Present?	Definition
0	0	xxxx	x	Set "Preamble Present?" to No; Idle
0	0	pqxs	x	Inband signaling <u>p</u> 0 = half-duplex 1 = full-duplex <u>q</u> 0 = link down 1 = link up <u>s</u> 0 = 10BASE-T 1 = 100BASE-TX
1	0	0000	No	CRS asserted but no data yet
1	0	0101	No	Set "Preamble Present?" to Yes; Decode data
1	0	xxxx	Yes	Packet Data
1	1	1010	x	False Carrier
1	1	0101	x	Symbol Error

The COL pin or connection is also eliminated, as this signal is represented by (TX_EN OR TX_ER) AND CRS.

Referring now to Fig. 4, a schematic diagram of a reduced pin interface 32' constructed in accordance with another embodiment of the invention is illustrated. In this embodiment,

interface 32' reduces the number of pins or connections in a GMII interface in a similar manner as described above. However, in this embodiment, the signal encoding and decoding techniques are applied to GMII signals.

5 Logically, GMII is identical to MII, and most of the signals used the same names. However, there are several differences. The GMII data path is byte-wide rather than nibble-wide. In conventional GMII signaling, this reduces the GMII clock from 250 MHz (if the data path were nibble-wide) to
10 125 MHz. In addition, the clock is sourced from the controller, rather than the transceiver as is the case with MII. This is done to eliminate timing errors due to propagation delays of the ICs and circuit tracers used implement the interface. A brief description of the conventional GMII signals is given below.

15 As shown in Fig. 4, TXD [7:0] is the byte-wide data transmission signal, which is synchronous with a Gigabit Transmit Clock (GTX_CLK) signal that runs at a nominal rate of 125 MHz for data transmission. A Transmit Enable (TX_EN) signal indicates when valid data is present on TXD lines, and a
20 Transmit Error (TX_ER) signal is used to propagate errors through a repeater in shared, half-duplex LANs. Both TX_EN and TX_ER are synchronous with GTX_CLK.

As for the receive signals, there is RXD [7:0], the byte-wide data receive signal which is synchronous with a Receive
25 Clock (RX_CLK) signal that is a recovered clock (125 MHz, nominal) from received data. A Receive Data Valid (RX_DV) signal indicates when valid data is present on the RXD lines, and a Receive Error (RX_ER) signal indicates that an error was detected while received data was being decoded. Both RX_DV and
30 RX_ER are synchronous with RX_CLK. These signals are illustrated in Fig. 4.

As shown in Fig. 4, there are two Ethernet control signals, both of which are asynchronous. A Carrier Sense (CRS) signal indicates when the physical layer channel is active, either with a received or transmitted signal. A Collision Detect (COL) signal indicates when one or more other stations are concurrently transmitting on the channel.

Management signals (not shown) include a Management Data Input/Output (MDIO) signal that is used to transmit and receive management information between the controller and transceiver. Also included is a Management Data Clock (MDC) used for management data exchange. There is also a VDC power supply (not shown).

The encoding/decoding scheme for the GMII signals, in accordance with this embodiment of the invention, is similar to that described above with respect to the MII signals in the previous embodiment, in that two control signals TX_CTRL and RX_CTRL are used to carry information previously carried on multiple signals. In this embodiment, TX_CTRL and RX_CTRL are each run at 250 Mb/s, with TX_CLK and RX_CLK being run at 125 MHz. The relationship between each of these CTRL signals and its corresponding CLK signal is illustrated by the timing diagram in Fig. 5. However, in this embodiment, TX_CTRL and RX_CTRL also encode for Carrier Extension and Carrier Extension with error data. In addition, the byte-wide data path is folded from 8 signals to 4 by running the data at twice the rate that it is normally run.

In this embodiment, MAC 22_n/22'_n and PHY 26_n/26'_n each include transmitter and receiver circuits for the interface signals, an encoder, a decoder, and a state machine controller. Each of these circuits is identified with the primed version of same reference numeral used to identify the corresponding component in the previous embodiment.

The folding of the incoming TXD [7:0] and RXD [7:0] signals to TXD [3:0] and RXD [3:0] signals respectively and unfolding of these nibble-wide data paths to the corresponding outgoing byte-wide data paths may be performed by appropriate circuitry embodied in MAC 22_n/22'_n and PHY 26_n/26'_n.

In accordance with this embodiment of the invention, the encoding/decoding of the transmit signals is as follows. TX_CTRL alternates between transmitting TX_EN and TX_ER, as in the previous embodiment. In a preferred embodiment, the encoding is as follows. When TX_CTRL is 0 during a full TX_CLK cycle, any data on the data lines is idle data. When TX_CTRL is 1 during one (e.g., the first) half of a TX_CLK cycle, the type of data on the data lines depends on the value of TX_CTRL during the other (e.g., the second) half of that TX_CLK cycle and the bits on the data lines. A TX_CTRL value of 0 during the other half of the TX_CLK cycle for any data on the data lines indicates that such data is packet data. A TX_CTRL value of 1 during the other half of the TX_CLK cycle with the data lines carrying a 0101 sequence means that such data is symbol error data. When TX_CTRL is 0 during one half of a TX_CLK cycle and 1 during the other half of that cycle, the meaning of the data on the data lines depends on the bits on the data lines. Data sequence 0111 indicates Carrier Extend data, while data sequence 1111 indicates Carrier Extend data with error. The encoding/decoding is summarized in the table below.

One (e.g., first) half of TX_CLK	Other (e.g., second) half of TX_CLK		
TX_CTRL	TX_CTRL	TXD [3:0]	Definition
0	0	xxxx	Idle
0	0	xxuv	Inband signaling <u>uv</u> 00 = 10BASE-T 01 = 100BASE-TX 10 = 1000BASE-T 11 = reserved
1	0	xxxx	Packet Data
1	1	0101	Symbol Error
0	1	0111	Carrier Extension
0	1	1111	Carrier Extension with Error

The encoding/decoding of the receive signals is also similar to that described in connection with the previous embodiment, in that the logical OR of RX_DV and CRS is carried by RX_CTRL in one (e.g., the first) half of a cycle of RX_CLK, and RX_ER is carried by RX_CTRL in the other (e.g., the second) half of that RX_CLK cycle. To distinguish between RX_DV and CRS, RXD [3:0] is decoded by the controller. Normally, CRS is asserted before RX_DV. Hence, during the time between assertion of CRS and assertion of RX_DV, RXD [3:0] should be 0000. Since a packet of data starts with a 0101 pattern, the assertion of RX_DV can be denoted by a transition of RXD [3:0] from 0000 to 0101. An error condition may occur which causes CRS to assert. This is known as a false carrier which can be denoted by a transition of RXD [3:0] from 0000 to 1010.

Carrier extension can be denoted by forcing the first half of RX_CTRL, which is RX_DV or CRS, to a low state and the second

One (e.g., first) half of RX_CLK	Other (e.g., second) half of X_CLK			
RX_CTRL	RX_CTRL	RXD [3:0]	Preamble Present?	Definition
0	0	xxxx	X	Set "Preamble Present?" to No; Idle
0	0	pqrs	x	Inband signaling <u>p</u> 0 = half-duplex 1 = full-duplex <u>q</u> 0 = link down 1 = link up <u>rs</u> 00 = 10BASE-T 01 = 100BASE-TX 10 = 1000BASE-T 11 = reserved
1	0	0000	No	CRS asserted but no data yet
1	0	0101	No	Set "Preamble Present?" to Yes; Decode subsequent data
1	0	xxxx	Yes	Packet Data
1	1	1010	X	False Carrier
1	1	0101	X	Symbol Error
0	1	0111	X	Set "Preamble Present?" to No; Carrier Extension
0	1	1111	X	Set "Preamble Present?" to No; Carrier Extension with error

As in the previously described embodiment, the COL pin or connection is also eliminated, as this signal is represented by (TX_EN OR TX_ER) AND CRS.

Although interface 32 is shown in connection with MII signals and interface 32' with GMII signals, either interface may be used for 10BASE-T, 100BASE-TX or 1000BASE-T, in either half- or full-duplex mode. To this end, both of the interfaces 32 and 32' employ inband signaling to avoid contention on TX_CLK, since PHY 26_n/26'_n sources TX_CLK in 10BASE-T and 100BASE-TX operation and MAC 22_n/22'_n sources it in 1000BASE-T operation. Such inband signaling allows the PHY to inform the MAC at what speed and on what duplex the link is operating. It also allows the MAC to inform the PHY that it is ready for operation at a certain speed and duplex. To prevent contention as to TX_CLK sourcing in 10/100 operation, the PHY will not source the TX_CLK until the uv bits from the MAC matches the rs bits sourced from the PHY. The inband signaling occurs when TX_CTRL is 0 for a full clock cycle and/or when RX_CTRL is 0 for a full clock cycle, as illustrated in the tables above.

An alternate embodiment for avoiding contention on TX_CLK allows TX_CLK to be unidirectional. In this alternate embodiment, MAC 22_n/22'_n sources TX_CLK at 2.5, 25 or 125 MHz. Hence, there is no possibility that of contention on TX_CLK.

Thus, for this alternate TX_CLK reconciliation technique, TX_CLK in interface 32 would point in the opposite direction in Fig. 3 (i.e., to the right). In Fig. 4, TX_CLK is already sourced by the MAC; thus, there would be no change in the TX_CLK signal direction in this figure. A transmit FIFO circuit in PHY 26_n/26'_n is used to reconcile data with the TX_CLK signal.

It should be noted that the invention is not limited to the specific encoding schemes identified above. Rather, other

encodings can be used. For example, TX_CTRL can be coded such that the 1/0 and 0/1 conditions are swapped. Similarly, RX_CTRL can be coded such that either the first or second 1/0 condition can be switched with either of the 1/1 conditions. This can be done because a "no error" case occurs more often than an "error" case. A 1/0 causes toggling on every cycle whereas a 1/1 does not. Coding of TX_CTRL and RX_CTRL in this manner also reduces power.

It should be readily apparent from the foregoing description that the present invention provides a network interface which reduces pin count by logically combining certain signals to eliminate redundancies, thereby enabling one pin to perform the functions previously performed by multiple pins. In particular, the present invention reduces the two connections previously used for TX_EN and TX_ER to a single TX_CTRL connection. Similarly, the invention reduces the three connections for RX_DV, CRS and RX_ER to a single RX_CTRL connection. The COL connection is also eliminated.

While the invention has been described in conjunction with specific embodiments, many further alternatives, modifications, variations and applications will be apparent to those skilled in the art in light of the foregoing description. For example, although the present invention has particular utility in connection with an Ethernet infrastructure operating in accordance with Ethernet standards and protocols, the invention is not so limited. The invention may also be employed with other network standards and protocols. Moreover, the present invention is not limited to the nominal 1 Gb/s data transmission rate and protocols. Thus, the invention described herein is intended to embrace all such alternatives, modifications, variations and applications as may fall within the spirit and scope of the appended claims.

WHAT IS CLAIMED IS:

1. A method of encoding signals for a network device, comprising the steps of:

- 5 transmitting a clock signal;
- forming a transmit control signal comprising in one half of a cycle of the clock signal a transmit enable signal and comprising in the other half of the cycle of the clock signal a transmit error signal;
- 10 transmitting the transmit control signal; and
- transmitting a data signal.

2. The method of claim 1, wherein when the transmit enable signal is asserted, the data signal comprises one of packet data and symbol error data.

3. The method of claim 2, wherein

 when neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises idle data;

 when the transmit enable signal is asserted and the transmit error signal is not asserted in a cycle of the clock signal, the data signal comprises packet data; and

 when both the transmit enable signal and the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises symbol error data.

4. The method of claim 3, wherein

 when the transmit enable signal is not asserted and the transmit error signal is asserted in a cycle of the clock signal, the data signal comprises one of carrier extension data and carrier extension data with error.

5. The method of claim 1, wherein the clock signal has a frequency of either 2.5 MHz, 25 or 125 MHz.

6. A method of decoding signals for a network device, comprising the steps of:

receiving a clock signal;

receiving a receive control signal;

decoding the receive control signal comprising in one half of a cycle of the clock signal a receive data valid signal or a carrier sense signal and in the other half of the cycle of the clock signal a receive error signal; and

receiving a data signal.

7. The method of claim 6, further comprising the step of decoding a preamble from the received data signal.

8. The method of claim 7, wherein

when the one half of the receive control signal is in a first state and the other half of the receive control signal is in the first state, the preamble is set to a first condition.

9. The method of claim 8, wherein

when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the first state, and the preamble is in a first condition, a carrier sense signal is in the second state.

10. The method of claim 8, wherein

when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the first state, the preamble is in the first condition, and the

received data signal comprises first predetermined data, then the preamble is set to a second condition and subsequent received data is decoded.

5 11. The method of claim 8, wherein
when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the first state, and the preamble is in a second condition, then the received data signal comprises packet data.

10

 12. The method of claim 8, wherein
when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the second state, and the received data signal comprises second predetermined data, then a false carrier is asserted.

0953316-0530000

 13. The method of claim 8, wherein
when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the second state, and the received data signal comprises first predetermined data, then a symbol error is asserted.

25

 14. The method of claim 8, wherein
when the one half of the receive control signal is in the first state, the other half of the receive control signal is in a second state, and the received data signal comprises one of third and fourth predetermined data, then the preamble is set to the first condition and a carrier extension is asserted.

30

 15. A method of decoding signals for a network device, comprising the steps of:
receiving a clock signal;

receiving a transmit control signal;

decoding the transmit control signal comprising in a half of a cycle of the clock signal a transmit enable signal and in the other half of the cycle of the clock signal a transmit error
5 signal; and

receiving a data signal.

16. The method of claim 15, wherein when the transmit enable is asserted, the data signal comprises one of packet data
10 and symbol error data.

17. The method of claim 16, wherein

when neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises idle data;
15

when the transmit enable signal is asserted and the transmit error signal is not asserted in a cycle of the clock signal, the data signal comprises packet data; and

when both the transmit enable signal and the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises a symbol error data.
20

18. The method of claim 17, wherein

when the transmit enable signal is not asserted and the transmit error signal is asserted in a cycle of the clock signal, the data signal comprises one of carrier extension data and carrier extension data with error.
25

19. The method of claim 15, wherein the clock signal has a frequency of either 2.5, 25 or 125 MHz.
30

20. A method of encoding signals for a network device, comprising the steps of:

transmitting a clock signal;

encoding a receive control signal comprising in one half of
5 a cycle of the clock signal a receive data valid signal or a carrier sense signal and in the other half of the cycle of the clock signal a receive error signal;

transmitting the receive control signal; and

transmitting a data signal.

10

21. The method of claim 20, further comprising the step of encoding a preamble for the data signal.

22. The method of claim 21, wherein

when a carrier sense signal is in a second state, the one
half of the receive control signal is set to the second state,
and the other half of the receive control signal is set to a
first state.

23. The method of claim 21, wherein

when a subsequent data signal containing packet data is to
be transmitted, the one half of the receive control signal is set
to a second state, the other half of the receive control signal
is set to a first state, and a current data signal is set to
first predetermined data.

25

24. The method of claim 21, wherein

when the data signal comprises packet data, the one half of
the receive control signal is set to a second state, and the
other half of the receive control signal is set to a first state.

30

25. The method of claim 21, wherein

when a false carrier is asserted, the one half of the receive control signal is set to the second state, the other half of the receive control signal is set to a second state, and the received data signal is set to second predetermined data.

5

26. The method of claim 21, wherein

10

when a symbol error is asserted, the one half of the received control signal is set to a second state, the second half of the receive control signal is set to the second state, and the receive data signal is set to first predetermined data.

27. The method of claim 21, wherein

15

when a carrier extension is asserted, the one half of the receive control signal is set to a first state, the other half of the receive control signal is set to a second state, and the received data signal is set to one of third and fourth predetermined data.

28. A network device, comprising:

20

a clock transmitter to transmit a clock signal;

an encoder to form a transmit control signal comprising in one half of a cycle of the clock signal a transmit enable signal and comprising in the other half of the cycle of the clock signal a transmit error signal;

25

a control signal transmitter to transmit the transmit control signal encoded by the encoder; and

a data signal transmitter to transmit a data signal.

30

29. The network device of claim 28, wherein when the encoder forms the transmit control signal on which the transmit enable signal is asserted, the data signal transmitter transmits

the data signal comprised of one of packet data and symbol error data.

30. The network device of claim 29, wherein

when the encoder forms the transmit control signal on which neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, the data signal transmitter transmits the data signal comprised of idle data;

when the encoder forms the transmit control signal on which the transmit enable signal is asserted and the transmit error signal is not asserted in a cycle of the clock signal, the data signal transmitter transmits the data signal comprised of packet data; and

when the encoder forms the transmit control signal on which both the transmit enable signal and the transmit error signal are asserted in a cycle of the clock signal, the data signal transmitter transmits the data signal comprised of symbol error data.

31. The network device of claim 30, wherein

when the encoder forms the transmit control signal on which the transmit enable signal is not asserted and the transmit error signal is asserted in a cycle of the clock signal, the data signal transmitter transmits the data signal comprised of one of carrier extension data and carrier extension data with error.

32. The network device of claim 28, wherein the clock signal has a frequency of either 2.5, 25 or 125 MHz.

33. A network device, comprising:

a clock receiver to receive a clock signal;

a control signal receiver to receive a receive control signal;

a decoder to decode the receive control signal comprising on one half of a cycle of the clock signal a receive data valid signal or a carrier sense signal and on the other half of the cycle of the clock signal a receive error signal; and

a data signal receiver to receive a data signal.

34. The network device of claim 33, wherein the decoder decodes a preamble from the received data signal.

35. The network device of claim 34, further comprising a state machine controller that

sets the preamble to a first condition, when the one half of the receive control signal is in a first state and the other half of the receive control signal is in the first state.

36. The network device of claim 35, wherein

when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the first state, and the preamble is in a first condition, a carrier sense signal is in the second state.

37. The network device of claim 35, wherein the state machine controller sets the preamble to a second condition and the decoder decodes subsequent received data

when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the first state, the preamble is in the first condition, and the received data signal comprises first predetermined data.

38. The network device of claim 35, wherein

when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the first state, and the preamble is in a second condition, then the received data signal comprises packet data.

5

39. The network device of claim 35, wherein

when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the second state, and the received data signal comprises second predetermined data, then a false carrier is asserted.

10

40. The network device of claim 35, wherein

when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the second state, and the received data signal comprises first predetermined data, then a symbol error is asserted.

15

41. The network device of claim 35, wherein the state machine controller sets the preamble to the first condition and a carrier extension is asserted

20

when the one half of the receive control signal is in the first state, the other half of the receive control signal is in a second state, and the received data signal comprises one of third and fourth predetermined data.

25

42. A network device, comprising:

a clock receiver to receive a clock signal;

a control signal receiver to receive a transmit control signal;

30

a decoder to decode the transmit control signal comprising in a half of a cycle of the clock signal a transmit enable

signal and in the other half of the cycle of the clock signal a transmit error signal; and

a data signal receiver to receive a data signal.

5 43. The network device of claim 42, wherein

when the decoder the decodes the transmit control signal on which the transmit enable signal is asserted, the data signal receiver receives the data signal comprised of one of packet data and symbol error data.

10 44. The network device of claim 43, wherein

when the decoder decodes the transmit control signal on which neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, the data signal receiver receives the data signal comprised of idle data;

when decoder decodes the transmit control signal on which the transmit enable signal is asserted and the transmit error signal is not asserted in a cycle of the clock signal, the data signal receiver receives the data signal comprised of packet data; and

when the decoder decodes the transmit control signal on which both the transmit enable signal and the transmit error signal are asserted in a cycle of the clock signal, the data signal receiver receives the data signal comprised of a symbol error data.

45. The network device of claim 44, wherein

when the decoder decodes the transmit control signal on which the transmit enable signal is not asserted and the transmit error signal is asserted in a cycle of the clock signal, the data signal receiver receives the data signal comprised of one of carrier extension data and carrier extension data with error.

46. The network device of claim 42, wherein the clock signal has a frequency of either 2.5, 25 or 125 MHz.

47. A network device, comprising:

a clock transmitter to transmit a clock signal;

an encoder to encode a receive control signal comprising on one half of a cycle of the clock signal a receive data valid signal or a carrier sense signal and on the other half of the cycle of the clock signal a receive error signal;

a control signal transmitter to transmit the receive control signal; and

a data signal transmitter to transmit a data signal.

48. The network device of claim 47, wherein the encoder encodes a preamble for the data signal.

49. The network device of claim 48, further comprising a state machine controller that

sets the one half of the receive control signal to a second state, and sets the other half of the receive control signal to a first state, when a carrier sense signal is in the second state.

50. The network device of claim 48, further comprising a state machine controller that

sets the one half of the receive control signal to a second state, sets the other half of the receive control signal to a first state, and sets a current data signal to first predetermined data, when a subsequent data signal containing packet data is to be transmitted.

51. The network device of claim 48, further comprising a state machine controller that

sets the one half of the receive control signal to a second state, and sets the other half of the receive control signal to a first state, when the data signal comprises packet data.

52. The network device of claim 48, further comprising a state machine controller that

sets the one half of the receive control signal to a second state, sets the other half of the receive control signal to the second state, and sets the received data signal to second predetermined data, when a false carrier is asserted.

53. The network device of claim 48, further comprising a state machine controller that

sets the one half of the received control signal to a second state, sets the second half of the receive control signal to the second state, and sets the receive data signal to first predetermined data, when a symbol error is asserted.

54. The network device of claim 48, further comprising a state machine controller that

sets the one half of the receive control signal to a first state, sets the other half of the receive control signal to a second state, and sets the received data signal to one of third and fourth predetermined data, when a carrier extension is asserted.

55. A network device, comprising:

means for transmitting a clock signal;

means for forming a transmit control signal comprising in one half of a cycle of the clock signal a transmit enable signal

and comprising in the other half of the cycle of the clock signal a transmit error signal;

means for transmitting the transmit control signal; and

means for transmitting a data signal.

5

56. The network device of claim 55, wherein when the transmit enable signal is asserted, the data signal comprises one of packet data and symbol error data.

10

57. The network device of claim 56, wherein

when neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises idle data;

when the transmit enable signal is asserted and the transmit error signal is not asserted in a cycle of the clock signal, the data signal comprises packet data; and

when both the transmit enable signal and the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises symbol error data.

15

20

58. The network device of claim 57, wherein

when the transmit enable signal is not asserted and the transmit error signal is asserted in a cycle of the clock signal, the data signal comprises one of carrier extension data and carrier extension data with error.

25

59. The network device of claim 55, wherein the clock signal has a frequency of either 2.5, 25 or 125 MHz.

30

60. A network device, comprising:

means for receiving a clock signal;

means for receiving a receive control signal;

means for decoding the receive control signal comprising in one half of a cycle of the clock signal a receive data valid signal or a carrier sense signal and in the other half of the cycle of the clock signal a receive error signal; and

5 means for receiving a data signal.

61. The network device of claim 60, further comprising means for decoding a preamble from the received data signal.

10 62. The network device of claim 61, wherein when the one half of the receive control signal is in a first state and the other half of the receive control signal is in the first state, the preamble is set to a first condition.

15 63. The network device of claim 62, wherein when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the first state, and the preamble is in a first condition, a carrier sense signal is in the second state.

20 64. The network device of claim 62, wherein when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the first state, the preamble is in the first condition, and the received data signal comprises first predetermined data, then the preamble is set to a second condition and subsequent received data is decoded.

25 65. The network device of claim 62, wherein when the one half of the receive control signal is in a second state, the other half of the receive control signal is in

the first state, and the preamble is in a second condition, then the received data signal comprises packet data.

66. The network device of claim 62, wherein

when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the second state, and the received data signal comprises second predetermined data, then a false carrier is asserted.

67. The network device of claim 62, wherein

when the one half of the receive control signal is in a second state, the other half of the receive control signal is in the second state, and the received data signal comprises first predetermined data, then a symbol error is asserted.

68. The network device of claim 62, wherein

when the one half of the receive control signal is in the first state, the other half of the receive control signal is in a second state, and the received data signal comprises one of third and fourth predetermined data, then the preamble is set to the first condition and a carrier extension is asserted.

69. A network device, comprising:

means for receiving a clock signal;

means for receiving a transmit control signal;

means for decoding the transmit control signal comprising in a half of a cycle of the clock signal a transmit enable signal and in the other half of the cycle of the clock signal a transmit error signal; and

means for receiving a data signal.

70. The network device of claim 69, wherein when the transmit enable is asserted, the data signal comprises one of packet data and symbol error data.

5 71. The network device of claim 70, wherein
when neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises idle data;

10 when the transmit enable signal is asserted and the transmit error signal is not asserted in a cycle of the clock signal, the data signal comprises packet data; and

when both the transmit enable signal and the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises a symbol error data.

15 72. The network device of claim 71, wherein
when the transmit enable signal is not asserted and the transmit error signal is asserted in a cycle of the clock signal, the data signal comprises one of carrier extension data and carrier extension data with error.

20 73. The network device of claim 69, wherein the clock signal has a frequency of either 2.5, 25 or 125 MHz.

25 74. A network device, comprising:
means for transmitting a clock signal;
means for encoding a receive control signal comprising on one half of a cycle of the clock signal a receive data valid signal or a carrier sense signal and on the other half of the
30 cycle of the clock signal a receive error signal;
means for transmitting the receive control signal; and
means for transmitting a data signal.

75. The network device of claim 74, further comprising means for encoding a preamble for the data signal.

5 76. The network device of claim 75, wherein
when a carrier sense signal is in a second state, the one half of the receive control signal is set to the second state, and the other half of the receive control signal is set to a first state.

10 77. The network device of claim 75, wherein

when a subsequent data signal containing packet data is to be transmitted, the one half of the receive control signal is set to a second state, the other half of the receive control signal is set to a first state, and a current data signal is set to first predetermined data.

15 78. The network device of claim 75, wherein

when the data signal comprises packet data, the one half of the receive control signal is set to a second state, and the other half of the receive control signal is set to a first state.

20 79. The network device of claim 75, wherein

when a false carrier is asserted, the one half of the receive control signal is set to the second state, the other half of the receive control signal is set to a second state, and the received data signal is set to second predetermined data.

25 80. The network device of claim 75, wherein

when a symbol error is asserted, the one half of the received control signal is set to a second state, the second half

of the receive control signal is set to the second state, and the receive data signal is set to first predetermined data.

81. The network device of claim 75, wherein

when a carrier extension is asserted, the one half of the receive control signal is set to a first state, the other half of the receive control signal is set to a second state, and the received data signal is set to one of third and fourth predetermined data.

82. An interface signaling protocol, comprising:

a transmit clock signal;

a transmit control signal comprising in one half of a cycle of the transmit clock signal a transmit enable signal and comprising in the other half of the cycle of the clock signal a transmit error signal; and

a transmit data signal.

83. The interface signaling protocol of claim 82, wherein when the transmit enable signal is asserted, the data signal comprises one of packet data and symbol error data.

84. The interface signaling protocol of claim 83, wherein

when neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises idle data;

when the transmit enable signal is asserted and the transmit error signal is not asserted in a cycle of the clock signal, the data signal comprises packet data; and

when both the transmit enable signal and the transmit error signal are asserted in a cycle of the clock signal, the data signal comprises symbol error data.

85. The interface signaling protocol of claim 84, wherein
 when the transmit enable signal is not asserted and the
 transmit error signal is asserted in a cycle of the clock signal,
 5 the data signal comprises one of carrier extension data and
 carrier extension data with error.

86. The interface signaling protocol of claim 82, wherein
 the clock signal has a frequency of either 2.5, 25 or 125 MHz.

10

87. An interface signaling protocol, comprising:
 a clock signal;

a receive control signal comprising in one half of a cycle
 of the clock signal a receive data valid signal or a carrier
 sense signal and in the other half of the cycle of the clock
 signal a receive error signal; and
 a receive data signal.

15
20
25
30

88. The interface signaling protocol of claim 87, wherein
 the receive data signal comprises a preamble.

89. The interface signaling protocol of claim 88, wherein
 when a carrier sense signal is in a second state, the one
 half of the receive control signal is set to the second state,
 25 and the other half of the receive control signal is set to a
 first state.

90. The interface signaling protocol of claim 88, wherein
 when a subsequent data signal containing packet data is to
 30 be transmitted, the one half of the receive control signal is set
 to a second state, the other half of the receive control signal

is set to a first state, and a current data signal is set to first predetermined data.

91. The interface signaling protocol of claim 88, wherein
 5 when the data signal comprises packet data, the one half of the receive control signal is set to a second state, and the other half of the receive control signal is set to a first state.

92. The interface signaling protocol of claim 88, wherein
 10 when a false carrier is asserted, the one half of the receive control signal is set to the second state, the other half of the receive control signal is set to a second state, and the received data signal is set to second predetermined data.

93. The interface signaling protocol of claim 88, wherein
 15 when a symbol error is asserted, the one half of the received control signal is set to a second state, the second half of the receive control signal is set to the second state, and the receive data signal is set to first predetermined data.

94. The interface signaling protocol of claim 88, wherein
 20 when a carrier extension is asserted, the one half of the receive control signal is set to a first state, the other half of the receive control signal is set to a second state, and the received data signal is set to one of third and fourth predetermined data.

95. A network device, comprising:
 a clock transmitter to transmit a first clock signal;
 30 an encoder to form a transmit control signal comprising in one half of a cycle of the clock signal a transmit enable signal

and comprising in the other half of the cycle of the clock signal a transmit error signal;

a control signal transmitter to transmit the transmit control signal encoded by the encoder;

5 a data signal transmitter to transmit a first data signal;

a clock receiver to receive a second clock signal;

a control signal receiver to receive a receive control signal;

10 a decoder to decode the receive control signal comprising on one half of a cycle of the clock signal a receive data valid signal or a carrier sense signal and on the other half of the cycle of the clock signal a receive error signal; and

a data signal receiver to receive a second data signal.

15 96. A network device, comprising:

a clock receiver to receive a first clock signal;

a control signal receiver to receive a transmit control signal;

20 a decoder to decode the transmit control signal comprising in a half of a cycle of the clock signal a transmit enable signal and in the other half of the cycle of the clock signal a transmit error signal;

a data signal receiver to receive a first data signal;

a clock transmitter to transmit a second clock signal;

25 an encoder to encode a receive control signal comprising on one half of a cycle of the clock signal a receive data valid signal or a carrier sense signal and on the other half of the cycle of the clock signal a receive error signal;

30 a control signal transmitter to transmit the receive control signal; and

a data signal transmitter to transmit a second data signal.

97. The method of claim 1, further comprising the step of inband signaling when neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal.

5

98. The method of claim 6, further comprising the step of inband signaling when the one half of the receive control signal is in a first state and the other half of the receive control signal is in the first state.

10

99. The method of claim 15, further comprising the step of inband signaling when neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal.

15

100. The method of claim 20, further comprising the step of inband signaling when the one half of the receive control signal is in a first state and the other half of the receive control signal is in the first state.

20

101. The network device of claim 28, wherein when the encoder forms the transmit control signal on which neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, then the encoder performs inband signaling.

25

102. The network device of claim 42, wherein when the decoder decodes the transmit control signal on which neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, then the decoder performs inband signaling.

30

103. The network device of claim 47, wherein when the encoder encodes the receive control signal which is not asserted on neither one half of the cycle of the clock signal nor on the other half of the cycle of the clock signal, then the encoder performs inband signaling.

104. The network device of claim 55, wherein when the means for forming forms the transmit control signal on which neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, then the means for forming forms inband signaling.

105. The network device of claim 69, wherein when the means for decoding decodes the transmit control signal on which neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, then the means for decoding performs inband signaling.

106. The network device of claim 74, wherein when the means for encoding encodes the receive control signal which is not asserted on neither one half of the cycle of the clock signal nor on the other half of the cycle of the clock signal, then the means for encoding performs inband signaling.

107. The network device of claim 42, wherein when the decoder decodes the transmit control signal on which neither the transmit enable signal nor the transmit error signal are asserted in a cycle of the clock signal, then the decoder performs inband signaling.

ABSTRACT

A network interface which reduces pin count in an MII or GMII system by logically combining certain signals to eliminate redundancies, thereby enabling one external connection or pin to perform the functions previously performed by multiple pins. In particular, the two connections previously used for TX_EN and TX_ER are reduced to a single TX_CTRL connection. Similarly, the three connections for RX_DV, CRS and RX_ER are reduced to a single RX_CTRL connection. The COL connection is also eliminated.




Fig. 1




Fig. 2




Fig. 3




Fig. 4

The timing diagram shows two signals over time. The top signal, labeled 'CTRL', is a square wave that alternates between a high state and a low state. The bottom signal, labeled 'CLK', is a square wave that alternates between a high state and a low state at a higher frequency than the CTRL signal. Both signals are shown as black lines on a white background.

Fig. 5

DECLARATION AND POWER OF ATTORNEY BY SOLE INVENTOR

I HEREBY DECLARE THAT:

My residence, post office address, and citizenship are stated next to my name in PART A hereof.

I believe I am the original, first, and sole inventor of the subject matter which is claimed and for which a patent is sought on the invention entitled:

REDUCED PIN GIGABIT MEDIA INDEPENDENT INTERFACE

the specification of which:

☒ is attached hereto.

I have reviewed and understand the contents of the above-identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is material to the examination of this application in accordance with Title 37, Code of Federal Regulations, §1.56.

I hereby claim priority benefits under Title 35, United States Code §119 of any foreign application(s) for patent or inventor's certificate listed in PART B hereof and have also identified in PART B hereof any foreign application for patent or inventor's certificate having a filing date before that of the application of which priority is claimed.

I hereby claim the benefit under Title 35, United States Code §119(e) and §120, of any United States application(s) listed in PART C hereof and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph by the first paragraph of Title 35, United States Code §112, I acknowledge the duty to disclose material information as defined in Title 37, Code of Federal Regulations §1.56 which occurred between the filing date of the prior application and any national or PCT international filing date of this application.

I hereby declare that all statements made herein of my knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application thereon.

I hereby appoint the following as my attorney or agent with full power of substitution to prosecute this application and transact all business in the United States Patent and Trademark Office connected therewith:

Eric B. Janofsky, Registration No. 30,759
Peter J. Dehlinger, Registration No. 28,006
Judy M. Mohr, Registration No. 38,563
LeeAnn Gorthey, Registration No. 37,337
Linda Judge, Registration No. 42,702
Michael L. Gencarella, Registration No. 44,703
Michael T. Gabrik, Registration No. 32,896
Gregory L. Heinkel, Registration No. 44,755

Please direct all telephone calls to Michael T. Gabrik at (650) 324-0880. Address all correspondence to:

**Iota Pi Law Group
Customer No. 22918**


DECLARATION AND POWER OF ATTORNEY BY SOLE INVENTOR

PART A: INVENTOR INFORMATION AND SIGNATURE

Full name of FIRST inventor: William Lo

Citizenship: U.S.A. Post Office Address: 20327 Clay Street
Cupertino, CA 95014

Residence (if different): Same

Inventor's Signature:  Date: 5/26/00

PART B: PRIOR FOREIGN APPLICATION(S)

Serial No.	Country	Filing Date	Priority Claimed
			<input type="checkbox"/> Yes
			<input type="checkbox"/> No

PART C: CLAIM FOR BENEFIT OF FILING DATE OF EARLIER U.S. APPLICATION(S)

Serial No.	Filing Date	Status
		<input type="checkbox"/> Patented
		<input type="checkbox"/> Pending
		<input type="checkbox"/> Abandoned